



Imagen semejante /  
Illustration similar

# ENDRESS

## Power Generators

### ESE 190 CW/AS

Order No. **333333**

#### Main features

Max. Output [LTP] [kVA/kW]	187,5/150
Prime power (PRP) [kVA/kW]	170/136
Nominal voltage [V]	220/127
Frequency [Hz]	60
Nominal current 3~ (PRP) [A]	492,06
Power factor cos (phi)	0,8
Main circuit breaker [Pole]	3

#### Measures and weight

Dimensions L x W x H [mm]	2940 x 1160 x 1680
Weight in kg ca.	1614
Fuel tank capacity [l]	200

#### Autonomy

Running time @ 75% PRP [h]	4,8
----------------------------	-----

#### Noise level

Sound power level LWA [db(A)]	93
Sound pressure level LPA (7 m) [db(A)]	78

#### Installation data

Total air flow [m <sup>3</sup> /min]	12,3
Exhaust gas flow @ LTP [m <sup>3</sup> /min]	32,22
Exhaust gas temperature @ LTP [°C]	488
Maximum back pressure [kPa]	10,132472

Technical data and illustrations are not binding. We assume no liability for misprints.

2024-6-18

ENDRESS Elektrogerätebau GmbH  
Neckartenzlinger Str. 39  
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0  
Fax.: +49 (0) 7123-9737-50  
www.endress-generators.de



Motor	
Brand	Cummins
Model	6BTAA5.9-G12(S0)_60
Emission regulation	Non Emission Certified
Nr. of cylinder and disposition	6
Cooling system	Water-cooled
Displacement [ccm]	5900
Compression rate	17,3:1
Engine output (COP) [kW]	112
Engine output (PRP) [kW]	140
Engine output (LTP) [kW]	155
CO2 emissions [g / kWh]	k.A. (Stage III)
CO2 test procedure	k.A. (Stage III)
RPM [U/min]	1800
RPM regulation	Electronic
Starting system	Electric starter
Electric circuit [V]	24
Battery [Ah]	100
Fuel	Diesel
Specific fuel consumption @ 75% PRP [g/kWh]	202
Oil capacity [L]	16,4
Coolant capacity [L]	10
Lube oil consumption @ PRP (max) [%]	0,1

LTP - Limited Power in continuous service as ISO 8528-1:2005. It is defined as the maximum power available, under the agreed operating conditions, for which the generating set is capable of delivering for up to 500 h of operation per year (whose no more than 300 for continuative use) with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. No overload capability is available.

PRP - Power in continuous service as ISO 8528-1:2005. It is defined as being the maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load when operated for an unlimited number of hours per year under the agreed operating conditions with the maintenance intervals and procedures being carried out as prescribed by the manufacturer. The permissible average power output over 24h of operation shall not exceed 70 % of the prime power.

COP - Base load (continuous) service as ISO 8528-1:2005. It is defined as being the maximum power which the generating set is capable of delivering continuously whilst supplying a constant electrical load when operated for an unlimited number of hours per year under the agreed operating conditions with the maintenance intervals and procedures being carried out as prescribed by the manufacturer. A 10% overload capacity is available for a period of 1 hour within a 12-hour period of operation.

Ratings definition (ISO-8528)

ESP - Emergency Standby Power: It is the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 h of operation per year with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. The permissible average power output over 24 h of operation shall not exceed 70 % of the ESP.

This CO2 measurement results from testing over a fixed test cycle under laboratory conditions a(n) (parent) engine representative of the engine type (engine family) and shall not imply or express any guarantee of the performance of a particular engine'.

of the performance of a particular engine'.

Technical data and illustrations are not binding. We assume no liability for misprints.

2024-6-18

ESE 190 CW/AS

Order No. 333333



**Power Generators**

Generator	
Brand	MeccAlte ECP34 2L4A
Alternator type	synchron
Insulation class	Klasse H
Voltage regulation	electronic
Protection Class [IP]	23
Poles	3
Frequency [Hz]	60
Frequency tolerance [%]	±1
Voltage tolerance [%]	1
Power factor cos (phi)	0,8
Efficiency @ 75% load [%]	94,9
Standard AVR	DSR
THD full load LL/LN [%]	1,7 / 1,8
THD no load LL/LN [%]	2,3 / 2,4
THF [%]	<2
Short Circuit Current Capacity [%]	>300

Technical data and illustrations are not binding. We assume no liability for misprints.

2024-6-18

**ENDRESS** Elektrogerätebau GmbH  
Neckartenzlinger Str. 39  
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0  
Fax.: +49 (0) 7123-9737-50  
[www.endress-generators.de](http://www.endress-generators.de)

