



ESE 606 HS-GT

Order No. **112303**

Main features

Alternator type	synchron
Max. Output 1~ [kVA/kW]	7.2/6.4
Continuous Power 1~ [kVA/kW]	6.0/5.5
Nominal voltage [V]	230
Nominal Current [A]	26,1
Power factor cos (phi)	0,9
Frequency [Hz]	50
Protection Class [IP]	23

Engine

Engine Type	HONDA GX390 / 11 HP
Design	1-cylinder 4-stroke OHV
Displacement [ccm]	389
Output 3000 rpm	6,4
CO2 emissions [g / kWh]	743
CO2 test procedure	k.A
Fuel	Petrol
Fuel tank capacity [l]	30
Fuel consumption @ 75% PRP [L/h]	1,9
Running time @ 75% PRP	15,8
Starting system	Recoil starter
Sound power level LWA [db(A)]	97
Sound pressure level LPA (7 m) [db(A)]	72
Weight in kg ca.	77
Dimensions L x W x H [mm]	800 x 538 x 576
Shockproof sockets	1 x 230 V/16 A 1 x CEE 230 V/32 A

This CO2 measurement results from testing over a fixed test cycle under laboratory conditions a(n) (parent) engine representative of the engine type (engine family) and shall not imply or express any guarantee of the performance of a particular engine'.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2025-7-21

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generator.com



ESE 606 HS-GT

Order No. 112303



Equipment features

Lack of oil automatic switch-off

Alternator overload protection

Honda OHV engines

Large fuel tank for long running times

Possible applications

230V

Electric tools up to

5400W

Gardening or construction equipment up to

3600W

Compressors or pumps up to

2800W

Special equipment - not retrofittable

Order No.

RCD protection switch incl. earthing kit

162 009

Accessories

Order No.

Wheel kit

161 000

Maintenance kit

164 029

laboratorio-olosuhteissa tehdyssä kiinteässä testisyklissä, eikä se ole tae yksittäisen moottorin suorituskyvystä".

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2025-7-21

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generator.com

