



ESE 1206 DHS-GT ES

Order No. **112022A**

Main features

Alternator type	synchron
Max. Output 3~ [kVA/kW]	13.9/11.1
Max. Output 1~ [kVA/kW]	9.2/8.3
Continuous Power 3~ [kVA/kW]	11.8/9.4
Continuous Power 1~ [kVA/kW]	6.9/6.2
Nominal voltage [V]	400/230
Nominal Current [A]	17/30
Power factor cos (phi)	0,8/0,9
Frequency [Hz]	50
Protection Class [IP]	23

Engine

Engine Type	HONDA GX630 / 21 HP
Design	2-cylinder 4-stroke OHV
Displacement [ccm]	688
Output 3000 rpm	14,2
CO2 emissions [g / kWh]	751
CO2 test procedure	k.A
Fuel	Petrol
Fuel tank capacity [l]	24
Fuel consumption @ 75% PRP [L/h]	3,2
Running time @ 75% PRP	7,5
Starting system	Electric starter
Sound power level LWA [db(A)]	96
Sound pressure level LPA (7 m) [db(A)]	71
Weight in kg ca.	165
Dimensions L x W x H [mm]	960 x 641 x 667
Shockproof sockets	1 x 230 V/16 A 2 x CEE 230 V/16 A 1 x CEE 400 V/16 A

This CO2 measurement results from testing over a fixed test cycle under laboratory conditions a(n) (parent) engine representative of the engine type (engine family) and shall not imply or express any guarantee of the performance of a particular engine'.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2025-7-21

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generator.com



ESE 1206 DHS-GT ES

Order No. 112022A



Equipment features

Lack of oil automatic switch-off
Alternator overload protection
Honda OHV engines
Large fuel tank for long running times
Compound regulated high performance generator
Remote start connection

Possible applications

	400V	230V
Electric tools up to	9300W	6100W
Gardening or construction equipment up to	6200W	4100W
Compressors or pumps up to	4700W	3100W
Inverter welding equipment up to a dia. of 3.25 mm		

Special equipment - not retrofittable

RCD protection switch incl. earthing kit	Order No. 162 009
--	-------------------

Accessories

Wheel kit	Order No. 161 007
Wireless remote control	162 024
Maintenance kit	164 032

laboratorio-olosuhteissa tehdyssä kiinteässä testisyklissä, eikä se ole tae yksittäisen moottorin suorituskyvystä".

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2025-7-21

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generator.com

